Configurando Modem D-Link 500B Velox Telemar

Efetuando Login no moden:

Abra seu navegador (Internet Explorer, Firefox, etc) e digite o endereço IP: 192.168.254.254



Vai abrir a tela de login abaixo



Então utilize:

Nome de usuário: TMAR#DLKT20060205 senha: DLKT20060205

🗿 DSL. Router - Hicrosoft Internet Explorer 📃 📃 🔀					
Arquivo Editar Exibir Eavoritos Ferramentas Algula					27
0 · 0 · 8 8 % P	***				
Endereco)	54/				
D-Link	and the second sec				
Building Networks for People		ADOL D	utor.		
		Abor ut	uter		
No.	Device Info				
	as a direct				
	Board ID:	DSL-SUUB			
Device Info	Software version: Bootloader (CEE) Version:	1.0.07.0.0			
Diagnostics	Bublidduer (CFE) Version: 1.0.3/-0.8				
Management	This information reflects the current status of your DSL connection.				
	Line Rate - Upstream (Kbp	s);	1		
	Line Rate - Downstream ()	(bps):			
	LAN IP Address:				
	MAC Address:				
	Default Gateway:				
	Primary DNS Server:				
	Secondary DNS Server:				
	Rei	ommend: 800x600 pixels, High	Color(16 Bits)		
🐌 Concluído					Internet

Clique em Advanced Setup





Preencha os campos com os seguintes valores:

VPI = 0 VCI = 33 Service Category = UBR Without PCR

Enable Quality Of Service $\sqrt{}$

Clique em next



Selecione a segunda Opção: PPP over Ethernet (PPPoE)

Encapsulation Mode : LLC/SNAP-BRIDGING

Clique em next

🚔 DSL Router - Hicrosoft Internet Explorer 🔹 🗖 🔀				
Arquivo Editar Exibir Eavori	tos Ferramentas Ajuda 🦧			
0 · 0 · 🗷 🗟 🟠 🖉	P 🛊 🙆 🗇 😓 🔯 - 📮			
Endereco 🛃 http://192.168.254.3	254/ 🗸 MicAfee SiteAdvisor •			
Enderson Device Info Advanced Setup WAN LAN NAT Security Routing DNS DSL Diagnostics Management	Attraction of the standard sector of the sector o			
	designed and inter- the course and			
Concluido	Recommenta autorato picera, High concerta anas			

Nessa tela coloque o login e senha do seu provedor

Exemplo:

No caso de empresa coloque o numero de telefone seguido do @telemar.com.br

PPP Username: 3111222334@telemar.com.br PPP Password: 3111222334

Se for usuário final coloque dessa maneira

PPP Username: seuemail@operadora.com.br PPP Password: suasenha

Não marque nenhuma das outras opções.

Clique em next



Nessa tela você marca as opções:

Enable NAT Enable IGMP Multicast Enable WAN Service

Clique em next

Pronto você terminou. Agora clique em **save e reboot** e aguarde uns 2 minutos para o modem estabilizar

Feito por: LORDSANSUI